



# Выключатель-разъединитель, низкое напряжение, 400 А, AC 690 V, NH1|NH2, AC22B, 3P, IEC

Каталог № EBV233SW0

## Программа поставок

|                                                      |   |   |                                                                                                              |
|------------------------------------------------------|---|---|--------------------------------------------------------------------------------------------------------------|
| Программа поставок                                   |   |   | Принадлежности к предохранителю                                                                              |
| Основная функция                                     |   |   | Выключатель-разъединитель                                                                                    |
| Область применения                                   |   |   | низкое напряжение                                                                                            |
| Номинальный ток                                      | I | A | 400                                                                                                          |
| Номинальное напряжение                               |   |   | AC 690 V                                                                                                     |
| Типоразмер                                           |   |   | NH1<br>NH2                                                                                                   |
| Категория применения                                 |   |   | AC22B                                                                                                        |
| Описание                                             |   |   | Крепление токовой шины 185 мм<br>однофазное переключение<br>двойные V-образные клеммы без V-образных зажимов |
| Защита                                               |   |   | IP30                                                                                                         |
| Количество полюсов                                   |   |   | 3P                                                                                                           |
| возможно использование для типоразмеров/оборудования |   |   | Предохранители NH1 и NH2                                                                                     |
| Стандарт/сертификат                                  |   |   | IEC                                                                                                          |
| Форма                                                |   |   | вертикально                                                                                                  |
| Стандарты/предписания                                |   |   | IEC 60947-1<br>IEC 60947-3                                                                                   |

## Технические характеристики согласно ETIM 6.0

|                                                                                                                                                                                                   |  |    |                          |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|----|--------------------------|
| Low-voltage industrial components (EG000017) / In-line fuse base (EC001046)                                                                                                                       |  |    |                          |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Fuse strip (ecl@ss8.1-27-37-14-02 [AKF059010]) |  |    |                          |
| Model                                                                                                                                                                                             |  |    | Fuse switch disconnecter |
| Double interrupting                                                                                                                                                                               |  |    | No                       |
| Rated permanent current Iu                                                                                                                                                                        |  | A  | 400                      |
| Distance between rail centre, 40 mm                                                                                                                                                               |  |    | No                       |
| Distance between rail centre, 50 mm                                                                                                                                                               |  |    | No                       |
| Distance between rail centre, 60 mm                                                                                                                                                               |  |    | No                       |
| Distance between rail centre, 100 mm                                                                                                                                                              |  |    | No                       |
| Distance between rail centre, 185 mm                                                                                                                                                              |  |    | Yes                      |
| Max. rated operation voltage Ue AC                                                                                                                                                                |  | V  | 690                      |
| Conditioned rated short-circuit current Iq                                                                                                                                                        |  | kA | 100                      |
| Type of electrical connection of main circuit                                                                                                                                                     |  |    | Cable clamp              |
| Number of poles                                                                                                                                                                                   |  |    | 3                        |
| Construction size fuse insert                                                                                                                                                                     |  |    | NH1, NH2                 |