



Держатель предохранителей, LV, 16 А, перем. ток 400 В, D01, 3Р, IEC,
подходящий провод 1,5 - 4 мм², монтаж с фиксацией

Каталог № TFRN01-SB

Abbildung ähnlich

Программа поставок

Программа поставок			Принадлежности к предохранителю
Основная функция			Держатель предохранителей
Область применения			низкое напряжение
Номинальный ток	I	A	16
Номинальное напряжение			AC 400 V
Типоразмер			D01
Описание			подходит для проводов сечением 1,5 - 4 мм ² монтаж с фиксацией
Количество полюсов			3Р
возможно использование для типоразмеров/оборудования			для предохранителя размера D01
Стандарт/сертификат			IEC

Технические характеристики согласно ETIM 6.0

Circuit breakers and fuses (EG000020) / D0-system fuse base (EC001644)			
Electric engineering, automation, process control engineering / Electrical installation, device / Safety fuse systems / Neozed fuse base (ecl@ss8.1-27-14-21-20 [ACN355008])			
Number of poles			3
Construction size			D01
Material			Porcelain
Version with cover			No
Mounting method			Screw mounting
Nominal rated voltage		V	400
Nominal rated current		A	16