

Ограничитель тока молнии SPI, тип В, 100кА



Тип **SPI-100/NPE**
Каталог № **263139**

Abbildung ähnlich

Bauartnachweis nach IEC/EN 61439

Технические характеристики для подтверждения типа конструкции			
Номинальный ток для указания потери мощности	I_n	A	0
Потеря мощности на полюс, в зависимости от тока	P_{vid}	W	0
Потеря мощности оборудования, в зависимости от тока	P_{vid}	W	0
Статическая потеря мощности, не зависит от тока	P_{vs}	W	0.03
Способность отдавать потери мощности	P_{ve}	W	0
Мин. рабочая температура		°C	-40
Макс. рабочая температура		°C	85
			0

Технические характеристики согласно ETIM 6.0

Earthing, lightning and surge protection (EG000021) / Lightning current arrester for power supply systems (EC000381)			
Electric engineering, automation, process control engineering / Protection installation, device (electric) / Surge protection device (inner lightning protection) / Lightning current arrester for power supply systems (ecl@ss8.1-27-13-08-02 [ACN272008])			
System configuration DC			No
System configuration IT			No
System configuration TN			No
System configuration TN-C			No
System configuration TN-C-S			No
System configuration TN-S			No
System configuration TT			No
System configuration other			No
Type of poles			1
Lightning impulse current (10/350)		kA	100
Nominal discharge surge current (8/20)		kA	100
Max. continuous voltage AC		V	260
Max. continuous voltage DC		V	0
Nominal voltage AC		V	0
Nominal voltage DC		V	0
Voltage protection level		kV	1.5
Voltage protection level L-N		kV	0
Voltage protection level N-PE		kV	0
Voltage protection level (DC+ - DC-)		kV	0
Voltage protection level (DC+/DC- - PE)		kV	0
Follow current extinguishing capability		kA	0
Specific energy (W/R)		kJ/Ohm	0
Mounting method			DIN rail (top hat rail) 35 mm
Construction size			2 modular spacing
Max. conductor cross section solid (solid, stranded)		mm ²	50
Max. conductor cross section flexible (fine-strand)		mm ²	35
With remote signalling contact			No

Exhausting		No
Signalling at the device		Optic
Category type 1		Yes
Integrated backup fuse		No
Suitable for outdoor use		No

Размеры

